

PAARD

Main Room
Light – Patchlist

Desk

1x MA GMA2 Light (latest software)
1x MA Expansion wing

All lights are controlled by Artnet (on request on DMX)

Artnet

ELC Node 8>	IP 2.0.1.1 – Subnet 255.0.0.0
MA GMA2 >	IP 2.0.1.2 – Subnet 255.0.0.0
Guest Desk >	IP 2.0.1.3 – Subnet 255.0.0.0

Line A	(universe 1):	Dimmer
Line B	(Universe 2):	Stage
Line C	(Universe 3):	Floor
Line D	(Universe 4):	Hall + Smoke
Line E	(Universe 5):	Free
Line F	(Universe 6):	Free
Line G	(Universe 7):	Free
Line H	(Universe 8):	Led Wall and Balcony

Stage – Intelligent

18x Martin Mac Quantum Profile (Basic Mode)
12x Martin Mac Aura XB (Basic Mode)
8x Martin Atomic (4 CH Mode)
4x CueLed CW5 Led Floodlight (Floor)
6x Showtec Shark one Wash Zoom RGBW (side light)

Stage – Conventioneel

3x Par64 ACL
4x 2-Lite 1,2 KW
8x Cateye

Stage – Data

3x DMX Out
1x Dimmer Breakout (8CH)

Roof Intelligent

14x Rush by Martin MH6 Wash

Smoke

1x MDG ATMe Hazer

Line A (Universe 1)

4x Chauvet Ovation E-260 WW Profile	Roof	DMX 101 – 107 – 113 – 119
-------------------------------------	------	---------------------------

8x Chauvet Ovation E-260 WW Profile	Roof	DMX 125 – 131 – 137 – 143 149 – 155 – 161 – 167
-------------------------------------	------	--

(if you not have the fixturefile you can patch deskchannels on 101, 107, 113.....etc. Only thing you not have strobo, dim fine or dimmercurve control)

6x Showtec Wash One Zoom RGBW	Stage	DMX 301 – 321 – 341 – 361 DMX 381 – 401
-------------------------------	-------	--

1x Breakout	Floor	DMX 1-8
-------------	-------	---------

Free Dimmer channels	Free	DMX 9-96
----------------------	------	----------

DMX 2 (Universe 2)

1. Martin Mac Quantum Profile	LX1	DMX 1	Basic Mode
2. Martin Mac Quantum Profile	LX1	DMX 20	Basic Mode
3. Martin Mac Quantum Profile	LX1	DMX 39	Basic Mode
4. Martin Mac Quantum Profile	LX1	DMX 58	Basic Mode
5. Martin Mac Quantum Profile	LX1	DMX 77	Basic Mode
6. Martin Mac Quantum Profile	LX1	DMX 95	Basic Mode
7. Martin Mac Quantum Profile	LX2	DMX 115	Basic Mode
8. Martin Mac Quantum Profile	LX2	DMX 134	Basic Mode
9. Martin Mac Quantum Profile	LX2	DMX 153	Basic Mode
10. Martin Mac Quantum Profile	LX2	DMX 172	Basic Mode
11. Martin Mac Quantum Profile	LX3	DMX 191	Basic Mode
12. Martin Mac Quantum Profile	LX3	DMX 210	Basic Mode
1. Martin Mac Aura XB Wash	LX1	DMX 229	Basic Mode
2. Martin Mac Aura XB Wash	LX1	DMX 243	Basic Mode
3. Martin Mac Aura XB Wash	LX1	DMX 257	Basic Mode
4. Martin Mac Aura XB Wash	LX1	DMX 271	Basic Mode
5. Martin Mac Aura XB Wash	LX2	DMX 285	Basic Mode
6. Martin Mac Aura XB Wash	LX2	DMX 299	Basic Mode
7. Martin Mac Aura XB Wash	LX2	DMX 313	Basic Mode
8. Martin Mac Aura XB Wash	LX2	DMX 327	Basic Mode
9. Martin Mac Aura XB Wash	LX2	DMX 341	Basic Mode
10. Martin Mac Aura XB Wash	LX2	DMX 355	Basic Mode
11. Martin Mac Aura XB Wash	LX3	DMX 369	Basic Mode
12. Martin Mac Aura XB Wash	LX3	DMX 383	Basic Mode
1. Martin Atomic	LX1	DMX 397	4-CH Mode
2. Martin Atomic	LX1	DMX 401	4-CH Mode
3. Martin Atomic	LX1	DMX 405	4-CH Mode
4. Martin Atomic	LX2	DMX 409	4-CH Mode
5. Martin Atomic	LX2	DMX 413	4-CH Mode
6. Martin Atomic	LX3	DMX 417	4-CH Mode
1x ACL	LX1	DMX 421	1 Deskchannel
1x ACL	LX2	DMX 422	1 Deskchannel
1x ACL	LX3	DMX 423	1 Deskchannel
1x 2-Lite Blinder	LX3	DMX 424	1 Deskchannel
1x 2-Lite Blinder	LX3	DMX 425	1 Deskchannel
1x 2-Lite Blinder	LX3	DMX 426	1 Deskchannel
1x 2-Lite Blinder	LX3	DMX 427	1 Deskchannel
4x Cateye	LX1	DMX 428 to 431	
4x Cateye	LX2	DMX 432 tot 435	

DMX 3 (Universe 3) Floor

1. Martin Mac Quantum Profile	Floor	DMX 1	Basic Mode
2. Martin Mac Quantum Profile	Floor	DMX 20	Basic Mode
3. Martin Mac Quantum Profile	Floor	DMX 39	Basic Mode
4. Martin Mac Quantum Profile	Floor	DMX 58	Basic Mode
5. Martin Mac Quantum Profile	Floor	DMX 77	Basic Mode
6. Martin Mac Quantum Profile	Floor	DMX 96	Basic Mode
1. Martin Atomic	Floor	DMX	4-CH Mode
2. Martin Atomic	Floor	DMX	4-CH Mode
1. Cueleled CW5 Floodlight	Floor	DMX	11-CH Mode
2. Cueleled CW5 Floodlight	Floor	DMX	11-CH Mode
3. Cueleled CW5 Floodlight	Floor	DMX	11-CH Mode
4. Cueleled CW5 Floodlight	Floor	DMX	11-CH Mode

(possible to change the mode to Generic RGBWA fixture, we use them in Tourmode 11 channels)

DMX 4 (Universe 4) Hall

1. Rush by Martin MH6 Wash	Roof	DMX 1
2. Rush by Martin MH6 Wash	Roof	DMX 15
3. Rush by Martin MH6 Wash	Roof	DMX 29
4. Rush by Martin MH6 Wash	Roof	DMX 43
5. Rush by Martin MH6 Wash	Roof	DMX 57
6. Rush by Martin MH6 Wash	Roof	DMX 71
7. Rush by Martin MH6 Wash	Roof	DMX 85
8. Rush by Martin MH6 Wash	Roof	DMX 99
9. Rush by Martin MH6 Wash	Roof	DMX 113
10. Rush by Martin MH6 Wash	Roof	DMX 127
11. Rush by Martin MH6 Wash	Roof	DMX 141
12. Rush by Martin MH6 Wash	Roof	DMX 155
13. Rush by Martin MH6 Wash	Roof	DMX 169
14. Rush by Martin MH6 Wash	Roof	DMX 184

1. MDG ATMe Hazer	Roof	DMX 505
-------------------	------	---------

DMX 5 (Universe 5) Free

DMX 6 (Universe 6) Free

DMX 7 (Universe 7) Free

DMX 8 (Universe 8) Led Houselight

1. Led RGBW 8-Bit	Wall Floor	DMX 1
2. Led RGBW 8-Bit	Wall Level 1	DMX 5
3. Led RGBW 8-Bit	Wall Level 2	DMX 9
4. Led RGBW 8-Bit	Balcony 1	DMX 13
5. Led RGBW 8-Bit	Balcony 2	DMX 17
6. Led RGBW 8-Bit	Floor	DMX 21

(not needed to patch this on your desk as we keep them on the GMA2)