

PAARD

PATCH LIST GROLSCH ZAAL

Desk

GrandMA3 Fullsize (Latest firmware)

sACN

ELC Node 8 IP 2.0.1.1

House Desk (MA3) IP 169.254.196.54 Priority 150

Guest Desk IP 2.0.1.3 priority 100

Universe 1 Front + side

Universe 2 LX1

Universe 3 LX2

Universe 4 LX3

Universe 5 Hall + haze

Universe 6 Free

Universe 7 Floor

Universe 8 Free

Nr.	Fixture Name	Location	DMX Address	Mode	Notes
1	Chauvet Ovation E-260 WW Profile	Front Bridge	1.001	6 CH	
2	Chauvet Ovation E-260 WW Profile	Front Bridge	1.007	6 CH	
3	Chauvet Ovation E-260 WW Profile	Front Bridge	1.013	6 CH	
4	Chauvet Ovation E-260 WW Profile	Front Bridge	1.019	6 CH	
5	Chauvet Ovation E-260 WW Profile	Front Bridge	1.025	6 CH	
6	Chauvet Ovation E-260 WW Profile	Front Bridge	1.031	6 CH	
7	Chauvet Ovation E-260 WW Profile	Front Bridge	1.037	6 CH	
8	Chauvet Ovation E-260 WW Profile	Front Bridge	1.043	6 CH	
9	Chauvet Ovation E-260 WW Profile	Front Bridge	1.049	6 CH	
10	Chauvet Ovation E-260 WW Profile	Front Bridge	1.055	6 CH	
11	Chauvet Ovation E-260 WW Profile	Front Bridge	1.061	6 CH	
12	Chauvet Ovation E-260 WW Profile	Front Bridge	1.067	6 CH	
1	Chauvet Rogue R1 Beamwash	Side Stage Left	1.101	15 CH	
2	Chauvet Rogue R1 Beamwash	Side Stage Left	1.116	15 CH	
3	Chauvet Rogue R1 Beamwash	Side Stage Left	1.131	15 CH	
4	Chauvet Rogue R1 Beamwash	Side Stage Right	1.146	15 CH	
5	Chauvet Rogue R1 Beamwash	Side Stage Right	1.161	15 CH	
6	Chauvet Rogue R1 Beamwash	Side Stage Right	1.176	15 CH	
1	Chauvet Color Strike M	LX1	2.301	74CH	
2	Chauvet Color Strike M	LX1	2.375	74CH	
3	Chauvet Color Strike M	LX2	3.301	74CH	
4	Chauvet Color Strike M	LX2	3.375	74CH	
5	Chauvet Color Strike M	LX3	4.301	74CH	
6	Chauvet Color Strike M	LX3	4.375	74CH	
1	Chauvet Strike Array 2	LX1	2.491	5CH	
2	Chauvet Strike Array 2	LX1	2.496	5CH	
3	Chauvet Strike Array 2	LX1	2.501	5CH	
4	Chauvet Strike Array 2	LX1	2.506	5CH	
5	Chauvet Strike Array 2	LX2	3.501	5CH	
6	Chauvet Strike Array 2	LX2	3.506	5CH	
7	Chauvet Strike Array 2	LX3	4.491	5CH	
8	Chauvet Strike Array 2	LX3	4.496	5CH	
9	Chauvet Strike Array 2	LX3	4.501	5CH	
10	Chauvet Strike Array 2	LX3	4.506	5CH	

Nr.	Fixture Name	Location	DMX Address	Mode	Notes
1	Chauvet Maverick force 2 Profile	LX1	2.001	50CH	
2	Chauvet Maverick force 2 Profile	LX1	2.051	50CH	
3	Chauvet Maverick force 2 Profile	LX1	2.101	50CH	
4	Chauvet Maverick force 2 Profile	LX1	2.151	50CH	
5	Chauvet Maverick force 2 Profile	LX2	3.001	50CH	
6	Chauvet Maverick force 2 Profile	LX2	3.051	50CH	
7	Chauvet Maverick force 2 Profile	LX2	3.101	50CH	
8	Chauvet Maverick force 2 Profile	LX2	3.151	50CH	
9	Chauvet Maverick force 2 Profile	LX3	4.001	50CH	
10	Chauvet Maverick force 2 Profile	LX3	4.051	50CH	
11	Chauvet Maverick force 2 Profile	LX3	4.101	50CH	
12	Chauvet Maverick force 2 Profile	LX3	4.151	50CH	
13	Chauvet Maverick force 2 Profile	Floor	7.001	50CH	
14	Chauvet Maverick force 2 Profile	Floor	7.051	50CH	
15	Chauvet Maverick force 2 Profile	Floor	7.101	50CH	
16	Chauvet Maverick force 2 Profile	Floor	7.151	50CH	
17	Chauvet Maverick force 2 Profile	Floor	7.201	50CH	
18	Chauvet Maverick force 2 Profile	Floor	7.251	50CH	
1	Chauvet Maverick force 2 Beamwash	LX1	2.201	25CH	
2	Chauvet Maverick force 2 Beamwash	LX1	2.226	25CH	
3	Chauvet Maverick force 2 Beamwash	LX1	2.251	25CH	
4	Chauvet Maverick force 2 Beamwash	LX1	2.276	25CH	
5	Chauvet Maverick force 2 Beamwash	LX2	3.201	25CH	
6	Chauvet Maverick force 2 Beamwash	LX2	3.226	25CH	
7	Chauvet Maverick force 2 Beamwash	LX2	3.251	25CH	
8	Chauvet Maverick force 2 Beamwash	LX2	3.276	25CH	
9	Chauvet Maverick force 2 Beamwash	LX3	4.201	25CH	
10	Chauvet Maverick force 2 Beamwash	LX3	4.226	25CH	
11	Chauvet Maverick force 2 Beamwash	LX3	4.251	25CH	
12	Chauvet Maverick force 2 Beamwash	LX3	4.276	25CH	

Nr.	Fixture Name	Location	DMX Address	Mode	Notes
1	Rush by Martin MH6	Hall bridge 1	5.001	14 channel	
2	Rush by Martin MH6	Hall bridge 1	5.015	14 channel	
3	Rush by Martin MH6	Hall bridge 1	5.029	14 channel	
4	Rush by Martin MH6	Hall bridge 1	5.043	14 channel	
5	Rush by Martin MH6	Hall bridge 2	5.057	14 channel	
6	Rush by Martin MH6	Hall bridge 2	5.071	14 channel	
7	Rush by Martin MH6	Hall bridge 2	5.085	14 channel	
8	Rush by Martin MH6	Hall bridge 2	5.099	14 channel	
9	Rush by Martin MH6	Hall bridge 2	5.113	14 channel	
10	Rush by Martin MH6	Hall bridge 2	5.127	14 channel	
11	Rush by Martin MH6	Hall bridge 3	5.141	14 channel	
12	Rush by Martin MH6	Hall bridge 3	5.155	14 channel	
13	Rush by Martin MH6	Hall bridge 3	5.169	14 channel	
14	Rush by Martin MH6	Hall bridge 3	5.183	14 channel	
1	Martin Mac Aura XB	Floor	7.301		
2	Martin Mac Aura XB	Floor	7.315		
3	Martin Mac Aura XB	Floor	7.329		
4	Martin Mac Aura XB	Floor	7.343		
5	Martin Mac Aura XB	Floor	7.357		
6	Martin Mac Aura XB	Floor	7.371		
7	Martin Mac Aura XB	Floor	7.385		
8	Martin Mac Aura XB	Floor	7.399		
1	MDG Atme	Hall Bridge side	5.501	3 channel	
1	LOOK Viper 2.6	Hall Bridge side	5.500	1 channel	